

# **TalkMaster™**

IP intercom system

## Software User Guide

For all IP-series 10/100  
Ethernet Intercoms  
Models IP-EWST, IP EWST-POE



# Table of Contents

<b>Welcome To TalkMaster .....</b>	<b>1</b>
Welcome .....	1
Release Notes .....	1
System Requirements .....	3
<b>Using TalkMaster .....</b>	<b>5</b>
TalkMaster Overview .....	5
TalkMaster Main Screen .....	6
Tool Bar .....	7
Intercom View / Custom View tab .....	8
Calls Waiting .....	10
Audio Player .....	10
Auto Response .....	10
Listen Mode .....	11
Listen button .....	12
Talk Mode .....	12
Talk / Page button .....	14
Paging Messages .....	14
System Events .....	15
Audio Archive .....	15
<b>Using Call Announcement .....</b>	<b>17</b>
Call Announcement .....	17
Incoming Call .....	18
<b>Preferences and Setup .....</b>	<b>19</b>
Preferences .....	19
Preferences - Options tab .....	19
Preferences - Multimedia tab .....	20
Preferences - Volume tab .....	21
Preferences - Legacy tab .....	22
Paging Groups .....	22
Paging Setup .....	23
Capture Audio Archive .....	24
Play Audio Archive .....	25
Managed Intercoms .....	26
<b>TalkMaster Console Forwarding .....</b>	<b>27</b>
Forward Intercoms .....	27
Retrieve Intercoms .....	27
Unattended Console .....	27
<b>TalkMaster Menu Options .....</b>	<b>29</b>
File Menu .....	29
View Menu .....	29
Tools Menu .....	29
Console Menu .....	30
Admin Menu .....	30
Help Menu .....	31

<b>Configuring Intercoms .....</b>	<b>33</b>
Configure Intercoms .....	33
Advanced Configuration .....	33
Intercom Configuration - TalkMaster Clients .....	34
Intercom Configuration - Direct Mode .....	37
Updating Firmware .....	39
NIC Firmware Updating .....	40
ICOM Firmware Updating .....	40
 <b>Intercom Configuration Tool Menu Options.....</b>	 <b>43</b>
Configuration File Menu.....	43
Configuration View Menu.....	43
Configuration Action Menu.....	43
Configuration Help Menu .....	43
 <b>Troubleshooting.....</b>	 <b>45</b>
Troubleshooting.....	45
Changing Recordings .....	45
 <b>Index.....</b>	 <b>47</b>

# Welcome To TalkMaster

## Welcome

Welcome To TalkMaster™ LE!

If you are upgrading from an earlier version of TalkMaster™, please review the Release Notes.

To setup and configure your IP-series intercoms, please review Configure Intercoms.

If you would like help on using TalkMaster, please review TalkMaster Overview.



## Release Notes

### TalkMaster™ Version 1.8 Released November, 2005

TalkMaster™ version 1.8 contains the following enhancements and corrections:

- All Setup functions have been moved to the password protected Admin menu
- New tabbed views on main screen allow display of all Intercoms or all Paging Groups and selected Intercoms.
- New function to setup software based Paging Groups for paging operations
- New option to create a Managed Intercom list to continuously detect and display disconnected Intercoms.
- Multiple consoles can simultaneously forward their Intercoms to a single console
- New color coded buttons used when TalkMaster is paging multiple intercoms
- Clicking the **Grp** column header automatically clears checkmark from all rows
- The Settings and Advanced tabs of the Preferences dialog have been renamed to the Volume and Legacy tabs respectively
- Preferences and settings are now stored at the PC level instead of the Windows User level

### TalkMaster™ Version 1.7 Released June, 2005

TalkMaster™ version 1.7 contains the following enhancements and corrections:

- New Paging Messages dialog with up to eighteen predefined messages
- New Password protected Paging Setup dialog
- Intercom Configuration Tool now sorts by Location Name/ICOM ID for easier setup
- GPIO 4 Mode supports new options for Relay controls\*
- Improved speed and reliability of Console Forward / Retrieve operations \*
- When "Hide when minimized " preference is set, clicking the 'X' in the upper right hand corner of the screen causes TalkMaster to minimize to the system tray instead of closing
- Intercom Configuration Tool prevents Intercom IP address from ending with 255 or 0
- Accessing the Play Audio Archive dialog requires the administrator password

- The Preference "Talk button enabled by mouse click and hold" has been renamed to "Hold down Talk button while speaking (PTT)"
- Corrected "Intercom configuration changes fail" when Windows Regional Options are not set to English
- Corrected "UDP Audio problems" when Windows Regional Options are set to Japanese
- Corrected "Multimedia Card Selection" when multiple cards are present in the PC

\* Use of this feature requires current Intercom Firmware. Please refer to our website (<http://www.aiphone.com>) for information on the current Firmware.

### **TalkMaster™ Version 1.6 Released January, 2005**

TalkMaster™ version 1.6 contains the following enhancements:

- Call Announcement mode with audio and visual notification of incoming calls
- Automatic removal of entries from the Calls Waiting queue when a call is completed
- The Calls Waiting Audio Player is automatically closed at the end of a call
- Ability to select a multimedia card used for the Speaker and Microphone operation

TalkMaster version 1.6 contains the following bug fixes:

- Applying Intercom configuration changes fails in non-U.S. localizations
- Talk VU meter does not work
- Intercom Startup Audio is not always played
- Spurious error messages occur during TalkMaster Startup
- "Details" column size under Calls Waiting is too narrow
- In Automatic mode, TalkMaster's Listen button can be turned off by pressing the Intercom's Call button
- Multiple Intercoms behind a NAT Firewall do not function properly in TalkMaster

### **TalkMaster™ Version 1.5.215 Released July, 2004**

TalkMaster™ version 1.5.215 contains the following enhancements:

- Simplified screen
- Password protected Intercom search and configure
- Console forwarding and retrieval
- Enhanced Audio Archive functions
- The Door Open function appears on the main screen
- Keyboard control of the Talk and Listen buttons

New firmware is available for the IP Intercoms. Units must be flashed with new firmware to accommodate the following features. Please refer to Configure Intercoms for details:

- Location names flashed into the Intercom

- Audio sent to multiple intercoms is sent as a single a UDP broadcast
- Console forwarding and retrieval
- Specify alternative IP addresses for intercom forwarding in the event of TalkMaster console failure
- Specify duration of time for activation of door/open relay within the IP Intercom

## **System Requirements**

To utilize all of the features of TalkMaster™, you need the following:

- Windows 98SE, Windows 2000, or Windows XP
- Pentium III 750mHz or faster
- 128 MB RAM (256 MB suggested)
- 50 MB Available Disk Space
- Windows supported Sound Card with microphone and speakers



# Using TalkMaster

## TalkMaster Overview

TalkMaster™ is a software program designed to work with Aiphone's IP-series Intercoms.

TalkMaster has two main functions. First, TalkMaster must be used to configure the IP address information and related features for your IP intercoms. TalkMaster searches for any Intercoms on your network and allows you to specify the IP address settings for each one.

The screenshot displays the TalkMaster software interface. On the left, a table lists intercoms with columns for Location Name, Icom ID, IP Address, and Details. Two intercoms are listed: Station 1036CE and Station 102790, both with IP Address 0.0.0.0 and 'No IP addr' in the details. Below the table, it shows 'This PC is: MPC003' and fields for IP (192.168.254.112) and Port (3000). A 'Search' button with a magnifying glass icon is also present. On the right, the 'Selected Intercom Setting' panel is shown, with 'Client' selected over 'Server-Peer'. It includes checkboxes for 'Assign IP automatically with DHCP' and 'Assign this PC address as client's server'. Fields for IP Address, Subnet Mask, Gateway, Port, and Location Name are provided, along with 'Exit', 'Cancel', and 'Apply' buttons.

Location Name	Icom ID	IP Address	Details
Station 1036CE	1036CE	0.0.0.0	No IP addr
Station 102790	102790	0.0.0.0	No IP addr

This PC is: MPC003  
IP: 192.168.254.112 Port: 3000  
Search


**Selected Intercom Setting**  
☒ Client ☐ Server-Peer  
☐ Assign IP automatically with DHCP  
IP Address: 0.0.0.0  
Subnet Mask: 0.0.0.0  
Gateway: 0.0.0.0  
Port: 0  
Location Name: Station 1036CE  
☐ Assign this PC address as client's server  
Server IP: 0.0.0.0 : 0  
Exit Cancel Apply

Secondly, TalkMaster allows multiple intercoms to connect to the software via TCP/IP so they can be monitored by the TalkMaster console operator. The audio from an intercom can be heard on the PC's speakers and the PC's microphone is used to send audio to an intercom. Calls can be initiated from any intercom to TalkMaster or from TalkMaster to any intercom.

The TalkMaster feature set includes the ability to:

- Queue and answer Incoming Calls
- Make Outgoing Calls
- Listen in
- Page Groups of Intercoms via microphone or pre-recorded wav files
- Activate an Intercom's on board relay to interface with door / gate controls
- Record incoming and outgoing audio
- Playback recorded audio
- Temporarily forward Intercoms to another TalkMaster console
- Send automatic pre-recorded wav files to Intercoms when the operator is busy or away
- Remotely control Intercom volume settings
- Report Online and Offline Intercom status





TalkMaster can listen for incoming calls in one of three "modes":

### **Call Announcement with audible and visual alerts**

In this mode, pressing the Intercom button notifies the TalkMaster operator by an audible and/or visual alert. The TalkMaster operator responds and controls the microphone at that intercom to enable user hands-free operation. To set up Call Announcement mode, check the box next to **Activate Call Announcement** in the menu Admin - Preferences - Options tab

### **Automatic mode**

In this mode, when an intercom user presses the button, their voice is used to notify the TalkMaster operator of the incoming call. The TalkMaster operator can respond and control the microphone to enable hands-free operation. To set up Automatic mode, select the Automatic option under Listen Mode on the main screen.


### **Manual mode**

In Manual mode, when an intercom user presses the button, their voice is used to notify the TalkMaster operator of the incoming call. The TalkMaster operator can respond and optionally allow the user to control the PTT button themselves. To set up Manual mode, select the Manual option under Listen Mode on the main screen.

## **TalkMaster Main Screen**

Before you can use your Aiphone IP Intercoms, they must be configured with IP address information. Please see Configure Intercoms.

The following sections describe the areas of the TalkMaster™ main screen.



- 1 Tool Bar
- 2 Intercom View / Custom View tabs
- 3 Calls Waiting Queue
- 4 Auto Response setting
- 5 Talk Mode setting
- 6 Audio Archive setting
- 7 Listen Mode setting
- 8 System Events window

## Tool Bar



Forward Intercoms to an alternate TalkMaster Console. Please see Forward Intercoms for details.



Retrieve Intercoms from an alternate TalkMaster Console. Please see Retrieve Intercoms for details.

Incoming Call  
Answer Later

The **Answer Later** button is displayed when the **Activate Call Announcement** option in menu Admin - Preferences - Options has been checked and a call is incoming.

- Activating the Talk or Listen buttons answers the call and removes the Answer Later button from the screen
- Pressing this button sends a message (i.e. "please hold") to the intercom and disables the Audible and Visual alerts, allowing the TalkMaster operator time to complete another task before answering the incoming call

## Intercom View / Custom View tab

The **Intercom View** tab shows you all Intercoms that have connected to TalkMaster™. The **Custom View** shows all Paging Groups that have been defined as well as any Intercoms that are not defined in a Paging Group. Both views have the same columns and TalkMaster operates the same way on either view. You will normally work out of one or the other view depending on your environment.

TalkMaster can be configured to hide the **Intercom View** or the **Custom View**. This option is available through menu **Admin → Preferences**.


**Intercom View** - is used when you require 2-way communication with your Intercoms and have limited or non-static paging group requirements.

Intercom View		Custom View				
	Grp	Location	Status	Address	Door/Gate	Notes
	<input type="checkbox"/>	Back Door Intercom	Connected	192.168.254.111	Open	
	<input type="checkbox"/>	Font Door Intercom	Connected	192.168.254.106	Open	
	<input type="checkbox"/>	Lunch Room Overhead Speaker	Connected	192.168.254.163		
	<input type="checkbox"/>	Office Overhead Speaker	Connected	192.168.254.164		
	<input type="checkbox"/>	Parking Lot - East Speaker	Connected	192.168.254.162		
	<input type="checkbox"/>	Parking Lot - West Speaker	Connected	192.168.254.113		

- The first column indicates Intercom's connection status. A Green ICON means Online, a Red ICON means Offline, an Orange ICON means at least one Intercom in a paging group is offline.
- **Grp** - Click the box to tag Intercoms with an "X" to create an ad hoc paging group. Intercoms in an ad hoc paging group are simultaneously sent audio when **Talk Mode** is set to **Group** or **All Active**. To clear all **Grp** checkmarks, click the **Grp** column heading
- **Location** - Identifies the Intercom by Name
- **Status** - Displays the Intercoms connection status
- **Address** - Displays the Intercoms IP address
- **Door/Gate** - Displays the button if the Intercom has a Door Relay option configured. Clicking the button will turn on the Door Relay for the amount of time that has been configured in the Intercom.
- **Notes** - Displays information about intercom communications

Single click anywhere on a row except the **Grp** column to select (highlight with a blue background) an Intercom for **Talk / Listen** operations. Only one Intercom can be selected at a time. Clicking the selected Intercom will de-select it.

Right clicking on an Intercom displays the following Intercom Options context menu



- **Send announcement to selected unit** - Click to send the wave file defined in menu **Admin** → **Preferences - Startup Audio** to the Intercom
- **Activity and Connection Details** - Click to display the duration of the Intercoms connection, the time it connected, the last time it received audio, the last time audio was sent to it, and the IP address and Port it used to connect to TalkMaster
- **Reset Connection** - Click to close the socket the Intercom is connected to and force it to reconnect to TalkMaster
- **Intercom ID#** - Shows the ICOM ID (last 6 digits of the MAC address)
- **OS Version:** - Shows the ICOM version, the Intercom option bits, the Intercom model, and the NIC Version
- **List when Offline/Do NOT list when Offline** - Click to toggle this feature. The **List when Offline** feature forces TalkMaster to remember this intercom and to report on it whether it is connected or not. The **List when Offline/Do NOT list when Offline** option only appears when TalkMaster's Admin menu has been enabled. Refer to Managed Intercoms for more information


**Custom View** - is used when you require static paging groups as well as 2-way Intercom communication. The Paging Groups are listed first and do not list any information in the Status, Address, or Door/Gate columns. Any Intercoms that have connected to TalkMaster and have not been defined in a Paging group will be listed next. You can also configure an Intercom to appear in the list even if it is defined in a paging group by checking **Display in Custom View Tab** of the Advanced Configuration Settings of the Intercom Configuration Tool.

Intercom View		Custom View				
	Grp	Location	Status	Address	Door/Gate	Notes
	<input type="checkbox"/>	Indoor Speakers				
	<input type="checkbox"/>	Outdoor Speakers				
	<input type="checkbox"/>	Back Door Intercom	Connected	192.168.254.111	Open	
	<input type="checkbox"/>	Font Door Intercom	Connected	192.168.254.106	Open	

Column definitions are the same as previously listed in this topic.

Single click on a Paging Group row to check the **Grp** column. Rows marked with an X in the **Grp** column are available for **Page**, **Chime** or **Play File** operations when **Talk Mode** is set to **Group**. Paging Groups cannot be selected (highlighted with a blue background) for **Talk / Listen** operations.

Right clicking on a Paging Group displays the following Paging Group context menu:



The connection status of each Intercom in the group is listed.

## Calls Waiting


This list shows calls that are waiting to be answered.

Calls Waiting	Details	Time
Front Door	message in at 07:57 AM	00:03

- If you single click on the entry, that intercom is selected in the **Intercom View / Custom View** allowing you to communicate with it
- If you double-click on it, the Audio Player pops up so you can play back the original call

## Audio Player

The Audio Message Player is automatically started by double-clicking on messages in the **Calls Waiting** list. It allows messages that have arrived while communicating with another intercom to be played back.




- Once you play the audio clip, the "Delete played files on exit" is automatically checked and clicking the X in the right hand corner closes the Audio Player and deletes the clip
- If you choose to leave the Audio Player open, you can delete a call by right clicking on it and selecting the Delete option
- If **Call Announcement** is activated, the audio clip is automatically deleted and the Audio Player closed when the call is completed

## Auto Response

The **Auto Response** function allows you to temporarily suspend the console's operation. This function can also be activated by using the menu **Console → Unattended Console**.



Once you check the **Unattended** box, a dialog pops up reminding you that this mode has been set.



Any intercom that tries to contact the console is sent a message indicating that no one is available to take their call. Please see Unattended Console for more information.

Clicking the **Cancel** button returns the console to normal operation.

## Listen Mode

The **Listen Mode** determines if the **Listen** button is automatically turned on when the **Talk** button is turned off.

If **Call Announcement** is enabled in menu **Admin → Preferences - Options**, this option is set to **Automatic** and cannot be changed.



When set to **Automatic**, the Listen button is automatically turned on when the **Talk** button is turned off. This allows the intercom user to operate in a "hands free" mode.

When set to **Manual**, the **Listen** button must be activated by the TalkMaster™ operator or by pressing the PTT button on the intercom.

This setting is saved between TalkMaster sessions.

### Example of using Listen mode Automatic

Please note that the following example uses the option of holding the **Space Bar** to activate the Talk button. Please see menu *Admin-Preferences-options tab* for an alternate method of controlling the Talk button

- Intercom user presses and holds the PTT button on one of the Intercoms and begins speaking.
- The Intercom is automatically selected in TalkMaster and the audio is played through the PC speakers.
- The Intercom user releases the PTT button when done speaking
- The TalkMaster operator responds by holding down the **Space Bar** on the keyboard and speaking into the microphone.
- When the TalkMaster operator releases the **Space Bar**, the **Talk** button is turned off and the **Listen** button is turned on. This action allows the Intercom user to operate "Hands Free"
- Each time the TalkMaster operator holds down the **Space Bar**, the Talk button is activated. When the **Space Bar** is released, the **Talk** button is turned off and the **Listen** button is engaged.
- To end the conversation with an Intercom, the TalkMaster operator presses the **Escape key** on the keyboard while the **Listen** button is active.

An important benefit of using **Automatic mode** is that other intercoms are precluded from interrupting your "conversation" because the **Talk** or **Listen** button is always active. TalkMaster will not interrupt a call if there is already one in progress. Any other intercom that tries to contact TalkMaster will be placed in the **Calls Waiting list**.

#### Example of using Listen mode Manual:

Please note that the following example uses the option of clicking and holding the **Space Bar** to activate the **Talk** button. Please see menu Admin - Preferences - Options for an alternate method of controlling the **Talk** button

- Intercom user presses and holds the PTT button on one of the Intercoms and begins speaking.
- The Intercom is selected in TalkMaster™ and the audio is through the PC speakers.
- The Intercom user releases the PTT button when done speaking
- The TalkMaster operator responds by holding down the **Space Bar** on the keyboard and speaking into the microphone..
- When the TalkMaster operator releases the **Space Bar**, the **Talk** button turns off. The TalkMaster operator can then click the Listen button or allow the Intercom user to respond by using the PTT button.
- To end the conversation with an Intercom, the TalkMaster operator presses the **Escape key** on the keyboard while the **Listen** button is active.

*In Manual mode, it is possible for another intercom to interrupt your conversation by pressing the PTT button when neither the Talk nor Listen button is active.*

### Listen button

The **Listen** button can be activated by the TalkMaster operator or by the PTT button on an Intercom. You may only listen to a single intercom at one time.



In TalkMaster, with **Listen Mode** set to **Automatic**, the **Listen** button can be toggled by:

- Deactivating the **Talk** button with the mouse or
- Pressing the **Escape** key on your keyboard
- Clicking the **Listen** button with the mouse

If **Talk Mode** has been set to **Group** or **All Active**, the **Listen** button is disabled and turns blue



### Talk Mode

The **Talk Mode** setting determines which intercom(s) will hear audio sent from TalkMaster™.





**Selected** - refers to the intercom currently highlighted in blue in the **Intercom View / Custom View** list. This option allows 2-way communication with a single Intercom.

**Group** - refers to any Intercom or Paging Group that has an **X** in the **Grp** column of the **Intercom View / Custom View** list. This option allows 1-way communication with any number of Intercoms.

**All Active** - refers to all currently connected Intercoms in the **Intercom View / Custom View** list. This option allows 1-way communication with all Intercoms.

Switching from **Selected** to either **Group** or **All Active** will automatically disable the Listen function and changes the **Talk** button to a blue **Page** button.



When using **Selected** mode, audio is sent to the Intercom using a single TCP/IP stream. This allows you to communicate with an Intercom located anywhere that you can connect to through TCP/IP.

When using **Group** or **All Active** modes, audio is sent to the Intercoms using a single UDP Broadcast stream. Since UDP Broadcasts are filtered by many routers, the **Group** and **All Active** options may only work on the current segment of a Local Area Network. Please refer to the TalkMaster installation CD for instructions on installing the UBAM™ software if you need to broadcast on multiple network segments.

Pressing the **Talk/Page**, **Chime**, or **Play File** button will send audio to the intercom(s) you have indicated.

**Play File** - Brings up the Paging Messages dialog. **Play File** changes to **Stop File** while a file is being set one or more intercoms. You can terminate the active file by clicking **Stop File**

To play a .wav file on the Intercom(s), audio files must be encoded in either 8khz 8-bit PCM or 16-bit uLaw format. Commercial or free software is available to create these formats.

**Chime** - plays the page.wav file from the iSupport subdirectory located under the TalkMaster™-ii3 program directory. Page.wav is a recording of four successive beeps that you can play to get someone's attention at an intercom(s).



**Talk/Page** will turn on the PC's microphone to send the audio to the Intercom(s). Please refer to Talk button for details.

## Talk / Page button

The **Talk/Page** button turns on the PC's microphone and allows you to speak to the intercom highlighted in blue in the **Intercom View / Custom View** list.



By default, the state of the **Talk** button is toggled by:

- Single clicking the **Talk** button with the mouse or
- Tapping the **Space Bar**

By checking the **Hold down Talk button while speaking (PTT)** box in menu Admin - Preferences - Options tab, the Talk button can be activated by:


- Clicking and holding the mouse on the **Talk** button or
- Pressing and holding the **Space Bar**

If **Talk Mode** is set to **Group** or **All Active**, the **Talk** button turns blue and changes to a **Page** button. Intercoms or Paging Groups must have an X in the Grp column to be sent a Page.



## Paging Messages

Clicking the **Play File** button brings up the **Paging Messages** dialog. The buttons on this screen are defined via the Paging Setup dialog.



When a button is pressed, the associated file is played to the Intercom(s) specified by the **Talk Mode**.

When a Paging button is pressed, the **Stop Message** button becomes active till the file has completed. Pressing the **Stop Message** button terminates file being played.


If the **OK** button is pressed you are returned to the main TalkMaster screen. If a file is still being played, the **Play File** button changes to **Play Stop** allowing you to terminate the recording.

*Please note that you cannot respond to any calls until the paging message has completed.*

If the **Find File** button is available, you can select a file of your choosing to play.

## System Events

The **System Events** window tracks activities from TalkMaster™. Information in this window can be used by Aiphone Technical Support for diagnosing support issues.



## Audio Archive

A checkmark in the **Audio Archive Capture** box indicates that TalkMaster is archiving speaker and microphone audio for playback at a later time. This function is controlled through the menu **Admin → Capture Audio Archive**. If TalkMaster's Admin menu has been enabled, you can also check/uncheck this box. Please refer to Capture Audio Archive for more information.



To play back archived audio, use the menu Admin → Play Archive Audio.



# Using Call Announcement

## Call Announcement

Call Announcement causes an audible and/or visual alert to be issued to the TalkMaster™ operator when the Call or PTT button on an intercom is pressed.

Selecting menu **Admin → Preferences** and checking **Activate Call Announcement** in the Options tab turns this option on. If this option is selected, **Listen Mode** is set to **Automatic** and is grayed out.

If the TalkMaster screen is minimized and the button on the Intercom is pressed, the Incoming Call dialog will be displayed.

If multiple Intercoms call in, they will be queued in a "first in - first out" basis.

If an Intercom user calls in when no calls are active, the **Answer Later** button appears on the tool bar. To answer the call immediately, the operator can activate either the **Talk** or **Listen** buttons. Answering the call removes the **Answer Later** button. Pressing the **Answer Later** button will acknowledge the Audible and Visual notifications and send a message (i.e. "one moment please") to the Intercom. This allows the TalkMaster operator to complete another task before answering the incoming call.

Example of using Call Announcement:


Please note that the following example uses the option of holding down the **Space Bar** to activate the **Talk** button and releasing the **Space Bar** to activate the **Listen** button as well as pressing the **Escape** key to end the call. Please see menu Admin - Preferences - Options tab for alternate methods of controlling the **Talk** and **Listen** buttons.

- A user presses and releases the "Call" or PTT button on the Intercom
- A short message (i.e. "your call is being connected") is returned to the Intercom.
- The Title Bar and the Icon in the Task Bar begin to flash and/or the audible notification is played at the TalkMaster console up to 4 times or until the operator engages the **Talk**, **Listen** or **Answer Later** button.
- An entry for the intercom is added to the Call Queue
- The Intercom is selected (highlighted with a blue background) in the Intercom View / Custom View
- The TalkMaster operator responds by holding down the **Space Bar** on the keyboard and speaking into the microphone.
- When the TalkMaster operator releases the **Space Bar**, the **Talk** button is turned off and the **Listen** button is turned on. This allows the Intercom user to operate "Hands Free"
- Each time the TalkMaster operator holds down the **Space Bar**, the **Talk** button is activated. When the **Space Bar** is released, the **Talk** button is turned off and the **Listen** button is engaged.
- To end the conversation with an Intercom, the TalkMaster operator presses the **Escape key** on the keyboard while the **Listen** button is active.
- The Intercom is de-selected in the Intercom View / Custom View
- The entry is deleted from the Calls Waiting list
- If another entry is in the Calls Waiting list, it is automatically selected so the TalkMaster operator can start the next call by pressing the **Space Bar**

*An important benefit of using **Call Announcement** is that any other intercom is prevented from interrupting your "conversation" because the **Talk** or **Listen** button is always active. TalkMaster will not interrupt a call if there is already one in progress. Any other intercom that tries to contact TalkMaster will be placed in the **Calls Waiting list**.*

## Incoming Call

The Incoming Call dialog appears when the **Activate Call Announcement** option has been selected in menu Admin - Preferences - Options tab and the TalkMaster screen has been minimized.



Clicking the **Answer Now** button with the mouse or pressing the Enter or Space Bar key brings up the main TalkMaster window.

Clicking the **Answer Later** button with the mouse sends a message (i.e. "one moment please") message to the Intercom, closes the dialog and turns off the Visual and Audible Alerts. This action allows the TalkMaster operator to complete another task before answering the incoming call. If the call is not answered within 30 seconds, the **Incoming Call** dialog will open again and the Visual and Audible alerts will be triggered. Clicking the TalkMaster Icon in the Windows Task Bar or System Tray restores the TalkMaster screen with the Intercom selected in the Intercom View / Custom View.

# Preferences and Setup

## Preferences

Preferences are used to specify various settings for TalkMaster™. This is accessed from the menu **Admin → Preferences**.

The Options tab is used to customize the way TalkMaster works.


The Multimedia tab is used to select the speaker and microphone devices

The Volume tab is used to change the Volume on an Intercom

The Legacy tab is retained for compatibility with older Intercoms

## Preferences - Options tab

The **Options** tab sets options that affect the behavior of all intercoms.



**Ping Interval** - sets how often TalkMaster™ will send a Ping command to the intercoms to verify the connection

**Startup Audio** - Determines if a beep or a wav file is played when the Intercom connects to TalkMaster™. If you select **Speech**, you can select from a variety of .wav files or record your own.

**Use beep tones at start and end of incoming calls** - When this option is checked a beep is inserted at the beginning and end of each audio segment.

**Hide when minimized** - When this option is checked TalkMaster is minimized to the Windows

System Tray when either the - or X  in the upper right hand corner of the screen are pressed.

To close TalkMaster, use menu **File → Exit** or right click on the TalkMaster ICON in the system tray and select Close Program

If you check this box, it is recommended that you also check **Activate Call Announcement** so that the Incoming Call dialog is displayed when TalkMaster is minimized. Otherwise, TalkMaster can only be recalled by double clicking the TalkMaster ICON in the system tray.

**Hold down Talk button while speaking (PTT)** - When this option is checked, the **Talk** button can be activated by pressing and holding down the Space Bar or by clicking on the **Talk** button and holding the mouse button down.

If this option is not checked, the Talk button can be activated/deactivated by single clicking the **Talk** button or tapping the Space Bar on your computer keyboard.

**Activate Call Announcement** - When this option is checked, the button on the Intercom is treated as a Call button. After pressing and releasing the Intercom's Call button, the message "your call is being connected" is played at the Intercom. The **Call Announcement Notifications** will then be triggered in TalkMaster. Please see Call Announcement for more details.

**Call Announcement Notification** - These notifications alert the TalkMaster operator to an incoming call. The alerts will be triggered up to four times at 5 second intervals until the incoming call is answered. If the TalkMaster operator is already on a call, the alerts will not be triggered.

**Visual Notification** - Checking this box causes the TalkMaster title bar and task bar icon to flash.


**Audible Notification** - Checking this box causes the selected audio file to be played at the TalkMaster console. Select the Door Bell or the Custom option from the list. If you select Custom, you can record over the custom\_announcement.wav file in the iSupport subdirectory of the TalkMaster program directory. *If you record a new wave file, it should only be one or two seconds long since the wav file will not be interrupted once it starts playing! See Changing Recordings for more information.*

**Record Audio in Call Waiting Queue** - If a call is added to the Calls Waiting queue, checking this box allows audio captured during the Intercom's initial button press to be made available for playback from the Calls Waiting Queue.

**Hide View Tab** - Checking either the **Intercom View** or **Custom View** allows you to present a single view to the TalkMaster Operator.


## Preferences - Multimedia tab

The **Multimedia** tab is used to select the multimedia device to be used for the speaker and microphone.



## Preferences - Volume tab

The **Volume** tab is used to make adjustments to individual Intercoms.



**Selected Intercom** - You can use the up and down arrows to select an Intercom from the list of intercom connected to TalkMaster™.



**Audio Volume** - sets the audio volume on the selected Intercom. This can be overridden at the Intercom by using the Volume Up and Volume Down buttons.

**Friendly Name (Alias)** - Displays the selected Intercom's Name.

## Preferences - Legacy tab

The **Legacy** tab is used to change configuration settings on individual Intercoms. It is retained for compatibility with legacy intercoms as these options are now included in the Configure Intercoms menu item. **This will only re-program Intercoms with an ICOM version of 1.8.1 or earlier.**

**Selected Intercom** - You can use the up and down arrows to select an Intercom from the list of intercoms connected to TalkMaster™.

Please refer to the Advanced Configuration section of the Intercom configuration tool for the definition of these options.

## Paging Groups

The Paging Groups screen is accessed via the menu **Admin → Maintain Paging Groups**. It allows you to create groups of Intercoms that you want to send audio to at the same time.


Paging Groups are normally created for units that only have speaker output.

Paging Groups are listed first in the Custom View tab.

- **To create a new Paging Group** - press the **New** button. "New Group" appears in the **Group Name** field. To specify a custom name, type over "New Group". Select an intercom from the left column and click the >> button to add it to your new group in the right hand column. Click **Save** when done.
- **To change an existing Paging Group** - use the "Select a group" drop down list to pick a group. Change the name by typing over it or use the >> and << buttons to add or remove Intercoms. Click **Save** when done.
- **Delete** - pick the Paging Group from the **Select a group** drop down list. Click the Delete button to permanently remove it
- **To exit this screen** - press **Done**
- **To cancel changes** - press the **Cancel** button instead of the **Save** button

## Paging Setup



The Paging Setup screen is accessed via the menu **Admin → Maintain Paging Messages**.




Up to 18 buttons can be associated with pre-recorded wav files for use in the Paging Messages dialog. Buttons can have one of four colors.

- Select a button "slot" and type in the text to be displayed on the button.
- Assign a color to the button, by clicking on one of the four choices.



- Click the Folder Icon  and select the wav file to be associated with the button. A folder icon with a green background  indicates that a file has been associated with this button.

*Please note: the file must be in 8kHz 8-bit PCM or 16-bit uLaw or it will not play on the Intercom. Commercial or free software is available to create these formats.*

- Click the Play button  to verify the audio recording.
- Checking the "**Allow Users to Select Files**" places a "**Find File**" button on the paging dialog, allowing the user to select a file of their own choosing.
- Clicking the **Undo** button, clears any changes that have been made in this session
- Clicking the **Reset** button clears all buttons
- Clicking the **Cancel** button closes the dialog without saving changes
- Click the **OK** button save any changes and closes the dialog

## Capture Audio Archive

This option will capture all audio data to the file system. It is activated from the menu **Admin → Capture Audio Archive** or by checking the box on the main display.



Each time microphone or speaker output is produced, a separate file is created using the following naming convention

XXX-YYYYYYYYYYYY-HHMMSS.wav where:

- **XXX - IN** for speaker audio, **OUT** for microphone audio
- **YYYYYYYYYYYY** - the twelve digit Ethernet MAC address of the intercom that was communicated with.
- **HHMMSS** - Hours, minutes and seconds of the day in 24 hour format
- **.wav** - standard PCM wave file format.


The files are stored under the TalkMaster-ii3/iArchive directory. Each day an additional sub-directory is created so all audio archives for that day are stored in a single directory. The directory name is formatted as YYYYMMDD where YYYY is the year, MM is the month and DD is the Day of the month.

**It is the user's responsibility for backing up and managing the size of the iArchive subdirectory!**

The Play Audio Archive function can be used to easily find and play audio files for any date and time.

## Play Audio Archive

The Play Audio Archive function allows you to select and play a series of audio clips that have been archived. It can be accessed from the menu **Admin → Play Audio Archive**.





Use the drop down boxes to select the month and year and then select a day. Any audio streams which have been recorded are shown with vertical lines above the hour of the day.

The green lines represent the start of microphone audio and the red lines represent the start of speaker audio. The blue bar indicates the current position for the **Play** button.

Click on a vertical bar and click **Play**. The audio will be played until you click **Stop** or the end of the day is reached. As the audio is played, the display changes to indicate which intercom the audio came from or was sent to.

If you want to skip backwards or forward between audio clips, use the << or >> keys.

## Managed Intercoms

TalkMaster™ allows you to create a list of managed Intercoms so you can always determine whether they are online or offline. When you start TalkMaster, all managed Intercoms are listed with a red ICON . As each Intercom connects, the ICON turns green .


To add an Intercom to TalkMaster's managed list, check the **List when offline** box in the **Intercom Configuration Tool**. This box is automatically checked when the **Assign this PC address as client's server** box is checked. The Intercom's unique ICOM ID is used to track the Intercom.

You can also configure an intercom by right clicking on it in the Intercom View / Custom View and selecting the **List when Offline** option.


If you need to remove an Intercom from the Managed Intercom list, you can right click on it in the Intercom View / Custom View and select the **Do NOT list when Offline** option.

You must be in Admin mode to activate the **List when Offline** / **Do NOT list when Offline** right click option.

If an Intercom is offline, its ICON will turn red.

	<input type="checkbox"/>	Parking Lot - West Speaker	Disconnected			
--	--------------------------	----------------------------	--------------	--	--	--

If one or more Intercoms within a **Paging Group** are offline, the Paging Group's ICON will turn yellow. Right clicking on the **Paging Group** will show all online and offline Intercoms for that group.


	<input type="checkbox"/>	Outdoor Speakers				
---	--------------------------	------------------	--	--	--	--

# TalkMaster Console Forwarding

## Forward Intercoms

The Forward Intercoms function allows one or more TalkMaster™ consoles to temporarily assign all of their intercoms to another PC running TalkMaster. This option can be accessed

from menu **Console → Forward Intercoms** or from Tool Bar ICON .



Once you forward the intercoms, the **Forward** Intercom window will stay open and the **Forward** button will change to **Return**. The Pressing the **Return** button will send a message to the alternate console indicating that the intercoms will be retrieved. If the alternate console does not respond within 15 seconds, you will be asked if you want to retrieve the intercoms anyway.

If you need to shut down the TalkMaster™ console while this dialog is open, the Intercoms will stay forwarded to the Alternate Console. To return the Intercoms to this console, you will need to use the menu **Console → Retrieve** when you open up TalkMaster the next time.


## Retrieve Intercoms

The Retrieve Intercoms function will retrieve Intercoms that have been forwarded with the Forward Intercoms or that have been automatically forwarded via the Fail Forward function. Only those Intercoms that have their default Server IP set to this TalkMaster™ console will be returned to this console. This option can be accessed from menu **Console → Retrieve**

**Intercoms** or from Tool Bar ICON .


## Unattended Console

Setting the TalkMaster™ software to Unattended mode makes the console temporarily unavailable. If the PTT button is pushed on an intercom, a message indicating that says "We are unavailable to take your call at this time" will be sent. This message can be changed by re-recording the unavailable.wav file in the iSupport subdirectory of the TalkMaster-ii3 directory. See Changing Recordings for details.



## TalkMaster Menu Options


### File Menu



The File menu has one option:

**Exit** - will end the TalkMaster™ server session.

### View Menu




The View menu has three options:

**Event Log** - allows you to display the TalkMaster™ event log and save it as a text file.

**Screen Position** - has two options:

- **Save current view** saves the current window size
- **Reset to default** - sets it back to the size that the product originally shipped with.

### Tools Menu



**Mic and Speaker Levels** - adjusts audio levels sent to and received from the intercoms. You can also change the source used for the **Talk/Page** button from the microphone to Internet/Line in which allows you to play other sources of audio through the intercoms.





### Adjust Levels


- **Microphone audio sent to intercoms** - with the radio button selected, adjusting the slider affects the Windows Microphone Recording volume
- **Internet or 'Line In' audio set to intercom** - no adjustment allowed
- **Audio from Intercoms (heard on this PC)** - with this radio button selected, two options are presented
  - **Master Volume** - adjusts the Windows Master volume control
  - **Volume from intercoms** - adjusts the Windows .wav file volume

**Common IP Ports** - is a list of commonly used port numbers. You may reference this if you need to change the standard ports used by TalkMaster™.

**Record program events to file** - should only be checked if directed by Aiphone Technical Support. Leaving this option checked for an extended period of time can cause TalkMaster™ performance to be affected.

**Reset All Connections** - will cause TalkMaster to drop all current IP connections to active intercoms and force them to reconnect to TalkMaster™.

## Console Menu



**Forward Intercoms** - brings up a dialog box allowing you to temporarily forward all of the active intercoms to another PC running TalkMaster™. Refer to Forward Intercoms for complete instructions.


**Retrieve Intercoms** - will retrieve any intercoms from other PC's running TalkMaster that have this PC's IP address assigned as their primary server to connect to. This can be used to retrieve intercoms that have been forwarded via the **Forward** command or by the Intercom's **Fail Forward** configuration to another console

**Unattended Console** - allows you to temporarily suspend the console's operation. Any intercom that tries to contact the console is notified that no one is available to take their call. A dialog pops up reminding you that this mode has been set. Clicking the **Cancel** button returns the console to normal operation.

This setting is saved between TalkMaster sessions.

## Admin Menu

The **Admin Menu** allows you to configure TalkMaster™ for your environment.



To activate all of the options on the **Admin Menu**, click **Enable Admin**. You will be asked to enter your Admin password (default is admin). The full Admin Menu will then be activated.



**Set Administrator Password** - brings up the **Change Administrator Password** dialog. You must enter your current Administrator password before entering a new one.

**Preferences** - opens up the Preferences dialog.

**Maintain Paging Groups** - brings up the Paging Groups dialog. This is used to group Intercoms together for paging purposes

**Maintain Paging Messages** - brings up the Paging Setup dialog. This is used to setup the Paging Messages dialog with pre-recorded messages.

**Configure Intercoms** - brings up the Intercom Configuration Tool. This is used to setup the intercoms with IP addresses, other configuration information and to load new firmware.

**Capture Audio Archives** - toggles on and off the capture of microphone and speaker audio.


**Play Audio Archives** - opens up a dialog that allows you to select audio archives for playback by date and time.

**Intercom OS Recovery** - is used to recover the ICOM firmware if the "Reload ICOM Firmware" message appears in the Notes column in the Intercom View.

**Check for new versions online** - is used to check for and perform online updates to the TalkMaster software from the Internet.

**Disable Admin** - hides all Admin menu options except for Enable Admin.

## Help Menu



**Help on using TalkMaster™** - Opens up Help

**Online Documentation** - Directs you to online documents on the Aiphone Web site

**Aiphone Website** - Directs you to the Aiphone homepage

**About** - Displays the current version information about TalkMaster

# Configuring Intercoms

## Configure Intercoms

When Intercoms are shipped from Aiphone, they do not have IP address information configured. To configure them, you must connect them to your network, install TalkMaster™ and select the menu **Admin → Configure Intercoms**.

The Intercom Configuration Tool will immediately search for all Aiphone intercoms connected to your current network segment. You must match the lcom ID displayed on the TalkMaster screen to the ID# printed on the back of the intercom and then configure the Intercom's IP address information and the IP address of the server it will connect to.

*If you have intercoms located in a different network segment, you may not find them since many routers filter out UDP Broadcasts. You can either install these intercoms on the current network segment or you can install a copy of TalkMaster in the other network segment to configure your intercoms. You may also refer to the TalkMaster installation CD for instructions on installing the UBAM™ software which will allow you to configure units across different networks.*

*A network segment is determined by looking at the subnet mask and the corresponding bits in the IP Address. For example, on IP Address 192.168.2.175 Subnet 255.255.255.0, the network segment is 192.168.2, and on IP Address 126.10.11.12 Subnet 255.0.0.0, the network segment is 126.*

To configure Intercoms to connect to TalkMaster™, see Intercom Configuration - TalkMaster Clients.

To configure two Intercoms to communicate with each other in Direct Mode, see Intercom Configuration - Direct Mode.

## Advanced Configuration

When the Advanced Configuration option is checked in the Intercom Configuration Tool **View Menu**, you can specify addition options for an IP Intercom.

If these options are grayed out, you have an intercom with legacy firmware. You can configure intercoms with legacy firmware from the main TalkMaster™ screen using the menu **Admin → Preferences** and selecting the Legacy tab. To update the firmware, see Updating Firmware.

**Fail Forward IP 1,2,3** allow you to specify up to three IP addresses of alternate TalkMaster consoles that this Intercom will attempt to connect to if it's current TalkMaster console becomes unavailable. If an Intercom has failed forward to an alternate IP and it's default TalkMaster console is restarted, the default TalkMaster console can reacquire the intercom by using the menu **Console → Retrieve Intercoms**.

**GPIO 4 Mode** allows you to specify how General Purpose I/O (GPIO) port 4 is used. On Intercom models IP-EWST and IP-EWST-POE, GPIO 4 is connected to a relay (dry contact). The normal state for GPIO 4 is logic high (+5 volts). When activated, it changes to logic low (0 Volts).

- **Factory Default** - This setting has no effect.

- **Door / Relay Output** - on IP Intercom models that include a relay (dry contact), the Door/Gate button will become visible in the Intercom View / Custom View. This option is used in conjunction with **Door Relay Activate** (see below) which sets the amount of time the relay will stay active
- **Logic Input** - used with custom developed applications to monitor other equipment.
- **Activate On MIC / Speaker** - Selecting this option turns on GPIO 4 when ever the Intercom's Microphone and/or Speaker are activated. When both **Mic** and **Speaker** are checked, the Intercom will wait for 1 second of inactivity before turning off GPIO 4. *Use of the **Mic** option requires the Intercom's OS Version to be 1.9.5.74Y or higher.*

**Remote Listen Disable** - disables the ability to remotely turn on the Intercoms Microphone. With this option set, the Intercom Operator must press the PTT button on the Intercom in order for the other end to listen to the Intercom.

**Default to Listen (Direct Mode)** - is only available if option **Set as Server-Peer** is enabled. Enables the Server-Peer intercom in Direct Mode to automatically turn on the remote Intercom's Microphone when the Intercoms connect.

**No Beep Tone After PTT Released** - turns off the soft beep that is played on the intercom after the PTT button is released

**Display in Custom View Tab** - will force the Intercom to appear in the Custom View tab, even if it is included within a Paging Group.

**Door Relay Activate** - on IP Intercom models that include a relay for opening a door or gate, this option sets the number of seconds that the intercom's relay will stay active when the Door/Gate button is pressed in the Intercom View / Custom View. This is used in conjunction with **GPIO 4 - Door / Relay Output**

## Intercom Configuration - TalkMaster Clients

### Configuring intercoms for use with TalkMaster (Point to Multi-Point)

This procedure configures Intercoms to connect to the IP address of the PC running TalkMaster™. This connection can be on a LAN, WAN or across the Internet.

*To configure two intercoms to connect to each other, please see Intercom Configuration - Direct Mode.*

From the main TalkMaster™ screen, select the menu **Admin → Configure Intercoms**. The system will scan the local network segment using a UDP Broadcast to find all IP Intercoms. New Intercoms will show up with IP addresses of zero. **The Icom ID displayed on the screen will match the ID# printed on the back of the Intercom.**

Location Name	Icom ID	IP Address	Details
▼	030DA4	0.0.0.0	No IP addr
▼	0310F7	0.0.0.0	No IP addr
Cafeteria Intercom	115934	192.168.254.1...	Client
Console 3	030C31	192.168.254.1...	Server
Employee Entrance	030C15	192.168.254.1...	Client
Main Entrance	102AF9	192.168.2.96	Client DHCP
Office Overhead Sp...	030C28	192.168.254.1...	Client
Parking Lot Speaker	030B0A	192.168.254.1...	Client
Pod 2 - Cell 2	030C2C	192.168.254.1...	Client
Pod 2 - Cell 3	030C27	192.168.254.1...	Client
Pod 2 - Cell 4	030C08	192.168.254.1...	Client
Pod 2 - Cell 5	030C3E	192.168.254.1...	Client

This PC is: MPC003  
 IP: 192.168.254.112 Port: 3000

Advanced Settings

Fail Forward IP 1: 0.0.0.0 : 0  
 Fail Forward IP 2: 0.0.0.0 : 0  
 Fail Forward IP 3: 0.0.0.0 : 0

GPIO 4 Control Mode  
☒ Factory Default  
☐ Door / Relay Control  
☐ Logic Input  
☐ Activate On ☐ Mic ☐ Speaker

☐ Remote Listen Disable  
☐ Default to Listen (Direct Mode)  
☐ No Beep Tone After PTT Released  
☐ Display in Custom View Tab  
 Door Relay Activate: 5

☒ Show when offline

Exit Cancel Apply

*If you have intercoms located in a different network segment, you may not find them since many routers filter out UDP Broadcasts. You can either configure these intercoms on the current network segment prior to installing them on the desired network or you can install a copy of TalkMaster in the other network segment to configure your intercoms. Refer to the TalkMaster installation CD for instructions on installing the UBAM™ software to configure units across different networks.*

Selected Intercom Setting

☒ Client ☐ Server-Peer ☐ Multi-Client

☒ Assign IP automatically with DHCP

IP Address: 192.168.254.128  
 Subnet Mask: 255.255.255.0  
 Gateway: 192.168.254.254  
 Port: 0  
 Location Name: Room 106

☐ Assign this PC address as client's server  
 Server IP: 192.168.254.15 : 3000

☒ Show when offline

Exit Cancel Apply

For **each** intercom that you want to configure, click on it and then set the options as follows:

- **Set as Client** - Click this option

- **Assign IP automatically with DHCP** - This option determines how the Intercom's IP address is assigned. The Intercom IP address information can be assigned as a Static IP address or can be dynamically assigned if your network has a DHCP server.

To use DHCP, check the box Assign IP automatically with DHCP.

*Your system MUST have DHCP assignment capability if you choose to use this option. If you are unsure do NOT use DHCP.*

To assign a Static IP address, uncheck the box **Assign IP automatically with DHCP** and fill in the **IP Address**, **Subnet Mask** and **Gateway**. The **Port** field does not have to be filled out.


- **Location Name** - Assign a descriptive text name that uniquely identifies the Intercom. This name will display in the main TalkMaster screen.
- **Assign this PC address as client's server** - This option determines the TalkMaster IP address that the Intercom will connect to.

Check **Assign this PC address as the client's server** to have the Intercom connect to this PC.

To specify a different TalkMaster console, uncheck the box and fill in the IP address and Port.

- **List when Offline** - forces TalkMaster to remember this intercom and to list it on the Intercom View and/or Custom View whether it is connected or not. This option can also be toggled by right clicking on Intercoms in the Intercom View / Customer View tabs. The **List when Offline/Do NOT list when Offline** option only appears when TalkMaster's Admin menu has been enabled. Refer to Managed Intercoms for more information
- **Apply** - This option will save your settings to the selected intercom. After applying changes to an intercom, the unit will be reset and will be unavailable for 10-15 seconds
- **Cancel** - This option cancels changes that have not been Applied
- **Exit** - This option closes the Intercom Configuration Tool screen and returns to the main screen *after you have completed configuring all intercoms.*


**This PC is: XXXXXXXX** - This option allows you to change the default Port number TalkMaster™ uses to listen for Intercom connections on. If you change this setting, it will be reflected in the **Assign this PC address as client's server**. Intercoms must be configured to connect to TalkMaster on this port.



The screenshot shows a configuration window with a label 'This PC is: MPC003' and a mouse cursor pointing at it. Below the label are two input fields: 'IP' containing '192.168.254.112' and 'Port' containing '3000'.

**Search** - will re-search the local area network for all Aiphone IP Intercoms so you can verify all of your changes. Please note, that if you **Apply** changes to an intercom, the unit will be unavailable for 10 -15 seconds. If an intercom does not appear in the list, try searching a second time.





If you need to change other options on the intercoms, make sure that you check menu **View → Advanced**. Refer to Advanced Configuration for details.

## Intercom Configuration - Direct Mode

### Configuring two intercoms in Client-Server mode (Direct Mode - No PC required)

This procedure configures two Intercoms to connect to each other. This connection can be on a LAN, WAN or across the Internet.

*To configure intercoms to connect to TalkMaster™, please see Intercom Configuration - TalkMaster Clients.*

From the main TalkMaster™ screen, select the menu **Admin → Configure Intercoms**. The system will scan the local network segment using a UDP Broadcast to find all IP Intercoms. New Intercoms will show up with IP addresses of zero. **The Icom ID displayed on the screen will match the ID# printed on the back of the Intercom.**

Location Name	Icom ID	IP Address	Details
▼	030DA4	0.0.0.0	No IP addr
▼	0310F7	0.0.0.0	No IP addr
Cafeteria Intercom	115934	192.168.254.1...	Client
Console 3	030C31	192.168.254.1...	Server
Employee Entrance	030C15	192.168.254.1...	Client
Main Entrance	102AF9	192.168.2.96	Client DHCP
Office Overhead Sp...	030C28	192.168.254.1...	Client
Parking Lot Speaker	030B0A	192.168.254.1...	Client
Pod 2 - Cell 2	030C2C	192.168.254.1...	Client
Pod 2 - Cell 3	030C27	192.168.254.1...	Client
Pod 2 - Cell 4	030C08	192.168.254.1...	Client
Pod 2 - Cell 5	030C3E	192.168.254.1...	Client

This PC is: MPC003  
 IP: 192.168.254.112 Port: 3000

Search

Advanced Settings

Fail Forward IP 1: 0.0.0.0 : 0 Fail Forward IP 2: 0.0.0.0 : 0 Fail Forward IP 3: 0.0.0.0 : 0	GPIO 4 Control Mode <input checked="" type="radio"/> Factory Default <input type="radio"/> Door / Relay Control <input type="radio"/> Logic Input <input type="radio"/> Activate On <input type="checkbox"/> Mic <input type="checkbox"/> Speaker	<input type="checkbox"/> Remote Listen Disable <input type="checkbox"/> Default to Listen (Direct Mode) <input type="checkbox"/> No Beep Tone After PTT Released <input type="checkbox"/> Display in Custom View Tab Door Relay Activate: 5
--	---	---

Selected Intercom Setting

☒ Client ☐ Server-Peer ☐ Multi-Client

☒ Assign IP automatically with DHCP

IP Address: 192.168.254.128  
 Subnet Mask: 255.255.255.0  
 Gateway: 192.168.254.254  
 Port: 0  
 Location Name: Room 106

☐ Assign this PC address as client's server  
 Server IP: 192.168.254.15 : 3000

☒ Show when offline

Exit Cancel Apply

*If you have intercoms located in a different network segment, you may not find them since many routers filter out UDP Broadcasts. You can either configure these intercoms on the current network segment prior to installing them on the desired network or you can install a copy of TalkMaster in the other network segment to configure your intercoms. You may also refer to the TalkMaster installation CD for instructions on installing the UBAM™ software which will allow you to configure units across different networks.*

Determine which of the two intercoms will be the **Server-Peer** and which will be the **Client**.



To set up the **Server-Peer**:

The screenshot shows the 'Selected Intercom Setting' dialog box with the 'Server-Peer' radio button selected. The 'Assign IP automatically with DHCP' checkbox is unchecked. The IP Address field contains '192.168.254.15', Subnet Mask is '255.255.255.0', Gateway is '192.168.254.254', Port is '0', and Location Name is 'Main Office'. The 'Assign this PC address as client's server' checkbox is unchecked, with Server IP set to '192.168.254.15' and Port to '3000'. The 'List when offline' checkbox is also unchecked. At the bottom are 'Exit', 'Cancel', and 'Apply' buttons.

- **Set as Server-Peer** - Click this option
- **Assign IP automatically with DHCP** - This option is automatically grayed out
- **Location Name** - This option is automatically grayed out
- **Assign this PC address as client's server** - Uncheck **Assign this PC address as the client's server** and enter a *fixed* IP address and the Port number of the Server-Peer. You can change the default Port of 3000 as long as you specify the same port in the **Client**.
- **List when Offline** - This option does not apply to Direct Mode
- **Apply** - This option will save your settings to the selected intercom. After applying changes to an intercom, the unit will be reset and will be unavailable for 10-15 seconds

To set up the **Client**:


The screenshot shows the 'Selected Intercom Setting' dialog box with the 'Client' radio button selected. The 'Assign IP automatically with DHCP' checkbox is checked. The IP Address field contains '192.168.254.128', Subnet Mask is '255.255.255.0', Gateway is '192.168.254.254', Port is '0', and Location Name is 'Room 106'. The 'Assign this PC address as client's server' checkbox is unchecked, with Server IP set to '192.168.254.15' and Port to '3000'. The 'Show when offline' checkbox is checked. At the bottom are 'Exit', 'Cancel', and 'Apply' buttons.

- **Set as Client** - Click this option
- **Assign IP automatically with DHCP** - The Intercom IP address information can be assigned as a Static IP address or can be dynamically assigned if your network has a DHCP server. To use DHCP, check the box **Assign IP automatically with DHCP**. *Your system*

***MUST have DHCP assignment capability if you choose to use this option. If you are unsure do NOT use DHCP.*** To assign an IP address, uncheck the box **Assign IP automatically with DHCP** and fill in the **IP Address**, **Subnet Mask** and **Gateway**. You do not have to fill out the **Port**.

- **Location Name** - the unique name you assign to this Intercom
- **Assign this PC address as client's server** - This is automatically unchecked so you can enter the IP address and Port number of the Server-Peer.
- **List when Offline** - This option does not apply to Direct Mode
- **Apply** - This option will save your settings to the selected intercom. After applying changes to an intercom, the unit will be reset and will be unavailable for 10-15 seconds

**Search** - You can re-search for Intercoms to verify all of your changes. Please note, that if you **Apply** changes to an intercom, the unit will be unavailable for 10 -15 seconds. If an Intercom does not appear in the list, try searching a second time.



The configured intercoms will look something like this:

Location Name	Icom ID	IP Address	Details
Main Exit	030C3A	192.168.254.128	Client DHCP
Main Office	030BED	192.168.254.15	Server

If you need to change other options on the intercoms, make sure that you check menu **View → Advanced**. Refer to Advanced Configuration for details.

**Exit** - This option closes the Intercom Configuration Tool screen

The **Server-Peer** will play a short beep and the Active and Link lights will turn solid on both intercoms indicating that they have made a connection.


## Updating Firmware

*Updating firmware should only be done under the direction of Aiphone Technical Support. Improperly flashing Intercoms can render the units inoperable.*

Intercoms must have minimum firmware levels of 1.9.5.66.1-xx.x-3.68.4 to use the following features:

- Console Forwarding
- UDP Broadcast
- Fail Forward IP addresses
- Door Relay Activation time
- Location Name Stored in Intercom

Intercoms shipped with TalkMaster™ include the most current firmware. To verify the firmware level, right click on an intercom in the main TalkMaster screen and view the OS version. In the following example, v1.9.5.66.8 is the ICOM version and 3.68.4 is the NIC version.



If you would like to update firmware in your intercoms, please contact Aiphone Technical Support to verify upgradeability and to obtain the current firmware. Please have the Intercom ID# and OS Version available for each intercom that you would like to upgrade.

In order to update NIC Firmware, see NIC Firmware Updating

In order to update ICOM Firmware, see ICOM Firmware Updating

## NIC Firmware Updating


*If you are going to perform a NIC firmware update, please consult with Aiphone Technical Support to verify upgradeability and to obtain the current firmware.* Please have the serial number and OS Version available for each intercom that you would like to upgrade.

In order to update the NIC firmware, you must configure the Intercom to connect to the copy of TalkMaster™ that you will be doing the update from. Please refer to Intercom Configuration - TalkMaster Clients.

It is strongly recommended that the update be done on a local area connection (LAN) instead of on a wide area connection (WAN) due to the critical nature of firmware updating.

Use the menu Admin → Configure Intercoms to open the Intercom Configuration Tool.

Click on the Intercom you wish to update and select menu Action → NIC Firmware Upload.



TalkMaster will connect to the Intercom and begin uploading the firmware. When the upload is completed, a dialog box will be presented informing you that the action was successful. Once you click OK, the screen will lock for 30 seconds while the firmware re-programming takes place.

**DO NOT TURN THE INTERCOM OFF WHILE THE FIRMWARE RE-PROGRAMMING TAKES PLACE!**

## ICOM Firmware Updating


*If you are going to perform an ICOM firmware update, please consult with Aiphone Technical Support to verify upgradeability and to obtain the current firmware.* Please have the serial number and OS Version available for each intercom that you would like to upgrade.

In order to update the ICOM firmware, you must configure the Intercom to connect to the copy of TalkMaster™ that you will be doing the update from. Please refer to Intercom Configuration - TalkMaster Clients.

It is strongly recommended that the update be done on a local area connection (LAN) instead of on a wide area connection (WAN) due to the critical nature of firmware updating.

Use the menu Admin → Configure Intercoms to open the Intercom Configuration Tool.

Click on the Intercom you wish to update and select menu Action → ICOM Firmware Upload.



TalkMaster will connect to the Intercom and begin uploading the firmware. When the upload is completed, a dialog box will be presented informing you that the action was successful. Once you click OK.

**DO NOT TURN THE INTERCOM OFF WHILE THE FIRMWARE IS UPLOADING!**




# Intercom Configuration Tool Menu Options

## Configuration File Menu



**Exit** - exits the Intercom Configuration Tool


## Configuration View Menu



**Common Port Assignments** - is a reference list of the common IP port settings

**Advanced** - makes the Advanced Settings section of the Intercom Configuration Tool available. Please see Advanced Configuration for details. This setting is remembered between TalkMaster™ sessions.

## Configuration Action Menu



**Search Boards** - will search the current network segment for IP intercoms


**Apply Settings** - saves changes made to the current intercom

**NIC Firmware Upload** - updates a portion of the IP intercom firmware. This option will only display if NIC firmware is present on your Hard Drive.

**ICOM Firmware Upload** - updates a portion of the IP intercom firmware. This option will only display if ICOM Firmware is present on your Hard Drive.

*Contact Aiphone Technical Support if you have any questions on Firmware updates.*

## Configuration Help Menu



**Help with Configuration Tool** - opens the Help window

**Test DHCP connections** - determines whether a DHCP server available on your network

**Aiphone Web Site** - opens the default web browser to the Aiphone homepage




# Troubleshooting

## Troubleshooting

### Intercom Configuration Tool cannot find Intercoms

- Verify that the ACTIVE or LD10 LED is on or flashing. If not, check the power connections.
- Verify that the LINK or LD9 LED is on. If not, verify the network cable between the Intercom and the network switch.
- Verify that the Intercoms are on the same network segment as TalkMaster™. TalkMaster uses a UDP Broadcast to search for Intercoms. Since most routers are configured to block UDP Broadcasts, you will not be able to configure the Intercoms in other networks. Perform the configuration in a single network, or install UBAM™ software from the TalkMaster Installation CD.
- If you have multiple network cards in the TalkMaster PC, verify that intercoms are connected to the card that TalkMaster has recognized. You can verify the IP address that TalkMaster is using by looking in the Intercom Configuration Tool under "This PC is: XXXXXXXX":



- If the Intercoms are configured for DHCP and no DHCP server is available, try re-powering the Intercom, wait 30 seconds, then try Searching 2 -3 times.
- If you cannot detect any intercoms using the Intercom Configuration Utility, connect the PC directly to the IP intercom *using a crossover cable*. Verify that you have a valid IP address, start TalkMaster and then try to Search for the Intercom again.
- You can also refer to the LED Indicator section in your hardware manual and review the diagnostic information presented there.

### Group, All Active functions do not work with Intercoms in other Networks

- If Intercoms are not in the same network as the TalkMaster, install the UBAM™ software off of the TalkMaster Installation CD. UBAM™ is a software product that will send/receive TalkMaster UDB Broadcast traffic between networks.

### Configured Intercoms do not connect to TalkMaster

- Incorrect subnet or gateway address in the Intercom. Re-configure the Intercom using the correct information.
- Incorrect Server IP address. Re-configure the Intercom using the correct information.
- Intercoms have been Forwarded or Fail Forwarded to a different IP Address. Use the Retrieve button to reset all intercoms to connect back to their default IP address.

### Resetting Intercom Configuration

- To reset an IP Intercom's configuration to factory defaults, unplug the power cord, press and hold the Talk and Volume Up buttons, plug the power cord in, wait 2 seconds and release the Talk and Volume Up buttons. A beep from the speaker indicates the intercom's configuration has been reset.

## Changing Recordings

You can change the audio wav files played in TalkMaster™ or sent to the Intercoms.

The wav files that are played at the TalkMaster console are used when Call Announcement is activated in the menu Admin - Preferences - Options and an incoming call is received. The



Audio Notification can be set to Doorbell or Custom. It is best to keep the recording to 1 or 2 seconds. Once it starts playing, it will play until it is done and will be repeated in 5 second intervals unless a keyboard operation or mouse click occurs.

Wave File	When Played	Verbiage
custom_announcement.wav	Call Announcement incoming call	custom
Doorbell_announcement.wav	Call Announcement incoming call	Chime

The wav files sent to the Intercoms must be encoded in either 8khz 8-bit PCM or 16-bit uLaw format. Commercial or free software is available to create these formats.

Wave File	When Played	Verbiage
announce.wav	Call Announcement greeting	Your call is being connected
announce_busy.wav	Call Announcement - TalkMaster Answer Later button pressed	Please Hold
End.wav	End of call from TM	beep
i_activated_au.wav	Intercom Connection to TalkMaster (Australian)	Intercom activated
i_activated_fr.wav	Intercom Connection to TalkMaster(French)	Intercom activated
i_activated_po.wav	Intercom Connection to TalkMaster (Portuguese)	Intercom activated
i_activated_uk.wav	Intercom Connection to TalkMaster (U.K.)	Intercom activated
i_activated_us.wav	Intercom Connection to TalkMaster (U.S.)	Intercom activated
in_page.wav	No longer used	Chime
page.wav	Chime button	bell
please_wait.wav	TalkMaster is on another call	Please hold while your call is being connected. Someone will get back to you as soon as possible
Start.wav	Start of call from TalkMaster	Beep
unavailable.wav	Unattended mode is set in TalkMaster	We are unavailable to take your call at this time

# Index

## A

Admin Menu	30
Advanced Configuration	33
Advanced Settings	43
Answer Later button	7, 18
Answer Now button	18
Assign IP	34, 37
Audio Archive	6, 15, 24, 25
Audio Archives	30
Audio Player	6, 10
Audio Volume	19, 29
Auto Response	6, 10, 27, 30
Automatic Mode	6, 11

## B

Beep Tone After PTT Released	33
------------------------------	----

## C

Call Announcement	17
Calls Waiting list	6, 10, 11
Capture Audio Archive	10, 24, 29
Changing Recordings	45
Client	34, 37
Client-Server	37
Common IP Ports	29, 43
Configure Intercoms	29, 33
Connected	26
Console Forwarding	27, 39

## D

DHCP	34, 37, 43
Direct Mode	33, 37
Disconnected	26
Door/Gate button	33

## E

Escape key	11, 12
Ethernet MAC	24
Event Log	29

## F

Fail Forward IP	27, 33, 39
Firmware	39
Flashing	39
Forward Intercoms	6, 27, 30

## G

Gateway	34, 37
GPIO	33

Group	6
Grp	6

## I

ICOM Firmware Upload	43
Icom ID	33, 34, 37
Incoming Call	18
Intercom Configuration	30, 33, 34, 37, 40, 43
Intercom OS Recovery	30
Intercom View / Custom View	6, 8, 33
Internet	34, 37
IP Address	33, 34, 37

## L

LAN	34, 37, 40
Legacy	22
Listen button	6, 11, 12, 33
Listen Mode	6, 11
Location Name	8, 34, 37
Logic Input	33

## M

Managed Intercoms	26
Manual Mode	11
Mic	5, 12, 14, 29
Monitor	33, 37
Mouse	19
MultiPoint	34

## N

Network Segment	33
New Intercoms	33, 34, 37
NIC Firmware Updating	40

## O

Online Documentation	31
Options	19, 33
OS Version	39, 40

## P

Paging	14, 23
Paging Groups	22, 30
Paging Messages	14, 23, 30
Paging Setup	14, 23
Password	30
Play Audio Archive	10, 25, 29
Play File	23
playback	25
Point-to-multipoint	34

<i>Point-to-point</i>	37
<i>Port</i>	33, 34, 37
<i>Preferences</i>	19, 30
<i>Preferences - Legacy tab</i>	22
<i>Preferences - Multimedia tab</i>	20
<i>Preferences - Options tab</i>	19
<i>Preferences - Volume tab</i>	21

## R

<i>Relay Output</i>	33
<i>Release Notes</i>	1
<i>Remote Listen Disable</i>	33
<i>Reset All Connections</i>	29
<i>Retrieve Intercoms</i>	27, 30

## S

<i>Screen Position</i>	29
<i>Search Boards</i>	34, 37, 43
<i>Selected Intercom</i>	8
<i>Server IP</i>	27, 33, 34, 37
<i>Server-Peer</i>	33, 37
<i>Set Administrator Password</i>	30
<i>Space Bar</i>	11, 14, 19
<i>Speaker Levels</i>	29
<i>Startup Audio</i>	19
<i>Static IP</i>	34, 37
<i>Subnet Mask</i>	33, 34, 37

<i>System Events</i>	6, 15
<i>System Requirements</i>	3

## T

<i>Talk button</i>	11, 14, 19, 27, 33, 37
<i>Talk Mode</i>	12
<i>TalkMaster Overview</i>	5
<i>Technical Support</i>	29, 40
<i>Test DHCP</i>	43
<i>Tool Bar</i>	7
<i>Tools Menu</i>	29
<i>Troubleshooting</i>	45

## U

<i>UBAM</i>	12, 33, 34, 37, 45
<i>UDP Broadcast</i>	12, 33, 34, 37, 39
<i>Unattended</i>	27

## V

<i>View Menu</i>	29
<i>Volume Down</i>	19, 21, 29
<i>Volume Up</i>	19, 21, 29

## W

<i>WAN</i>	34, 37, 40
<i>Wav</i>	19, 24, 27, 45
<i>Web site</i>	31

---

© Copyright 2005 Digital Acoustics, All Rights Reserved. TalkMaster™LE and ii3 are trademarks of Digital Acoustics Corporation, 263 Market Square, Lake Forest, IL 60045. Digital Acoustics® is a registered trademark. Microsoft Windows is a registered trademark of Microsoft Corporation in the United States, and/or other countries