

5 OPERATIONS

■ Conference Call

1. Initiator station presses a station # and **PAGE** button.
2. Repeat process up to 5 stations.
3. Depress and hold down **TALK** button, and begin speaking.
4. Respondant holds down **TALK** button to speak.
5. To get out of the Conference, participants press **OFF** button or hang up.
6. At conclusion, initiator presses **OFF** button or hang up.

■ Absence Memory

1. Before you leave your desk, press **MEMORY**, **MEMO** buttons.
2. When other station has pressed **MEMORY** button for call back, call-in LED starts blinking on your station.
3. Upon your return, press **MEMORY** button. You're connected to a first caller (in the order of youngest number).
4. After concluding with **OFF** button, press **MEMORY** button.
5. Repeat process until red LED goes out.
6. To cancel Absence memory; Press **MEMORY**, **0** buttons.

■ Camp-on Absence

When quick and high intermittent is heard upon dialed, press **MEMORY** button to leave a request for call back.

■ Memory Clear

To erase all memory functions present, press **MEMORY**, **0** buttons. i.e. Memory functions: Camp-on busy, Secretary transfer, Camp-on absence, Absence memory, except Privacy.

■ Group Call

1. Press **PAGE**, Group # (5 ~ 8) buttons.
*Press **PAGE** button again for call back.*
2. Announce through station speakers of one group, holding down **TALK** button.
3. **Within 40 seconds**, paged person at the nearest station of the group, presses **5**, **PAGE** buttons.
4. At conclusion, press **OFF** button.

■ All Call

1. Press **PAGE**, **0** buttons.
*Press **PAGE** button again for call back.*
2. Announce through all station speakers, holding down **TALK** button.
3. Press **5**, **PAGE** buttons to reply at the nearest station within 40 seconds.
4. At conclusion, press **OFF** button.

Paging

■ Zone Page

1. Press **PAGE** button, zone # (1 ~ 4) buttons.
*Press **PAGE** button again for call back.*
2. Page holding down **TALK** button.
3. Paged person presses **6**, **PAGE** buttons at nearest station.
4. To conclude, press **OFF** button.

■ Zone Talkback Page

1. Press **PAGE**, zone # (1 ~ 4) buttons.
2. Page holding down **TALK** button.
3. Release **TALK** button to listen.
4. To conclude, press **OFF** button.

■ All Page

1. Press **PAGE**, **9** buttons.
*Press **PAGE** button again for call back.*
2. Page holding down **TALK** button.
3. Paged person presses **6**, **PAGE** buttons at the nearest station.
4. To conclude, press **OFF** button.

Note: Talkback is not available in All Page mode.