

# PS-POE


## PoE Splitter

### -INSTRUCTIONS-

The PS-POE is a PoE splitter that provides a 24V DC output to power the strobe light in Aiphone's wall boxes and towers. The IX Series emergency stations have a secondary PoE output (pass-through) that can be used to connect to this splitter. The PoE pass-through will only be usable if the IX station is connected and powered via a PoE+ switch.

### WIRING

Drawing not to scale



<sup>1</sup> Connect the ground terminal to an Earth ground.

<sup>2</sup> Relay 1 must be enabled during the station programming process.

### SPECIFICATIONS

Power:	PoE (803.2af)
Power consumption:	8.4W
Output power:	24V DC, 350mA
Operating Temperature:	-40° ~ 140° F (-40° ~ 60°C)
Mounting:	Secure to mounting studs on back of IX station or secure to a 1-gang box.
Dimensions:	4-1/16" H x 2-9/16" W x 1-1/8" D